

Bently Nevada Service Manual

2300/25_KIT-003-00

1. Description

Manufacturer : Bently Nevada

3. Product Information

Manufacturer : Bently Nevada

Product No : 2300/25_KIT-003-00

Product type : 2300/25 Bently Nevada 2300/25 Condition Monitoring System Kit

Configuration : 003

2 Sensors

1-2300/25 Monitor

1-6 ft. (1.8 m) shielded Ethernet
cable

2-Accelerometer sensors

(200350)

2-12 ft. (3.6 m) cables (9571)

(Excluding Keyphasor sensor

and 24 Vdc power supply

Inputs

Power Input

DC Input 18~36 Vdc, max 7.5 W

Channel Types

ICP Accelerometers

Configurable

Bandpass filter

0.2 Hz to 20 kHz

Scale Factor

range

5 to 1000 mV/g

Full scale range 2 to 80 g peak

Current Sink

Source

3.3 mA $\pm$ 5%

Open Circuit

Voltage

-21 to -24 Vdc

Velocity

Configurable

Bandpass filter

0.2 Hz to 20 kHz

Scale Factor

range

5 to 1000 mV/in/s

Full scale range 0 to 50 in/s peak

Radial Vibration

Configurable

Bandpass filter

0.2 Hz to 20 kHz

Scale Factor

range

5 to 1000 mV/mil

Full scale range 0 to 160 mil peak-peak

Thrust Channel

Scale Factor

range

5 to 1000 mV/mil

Channel Types

Process Variable Channel

Support most of unit with default on

Temperature

Channel Hardware Specification

Configurable

Upper OK limit

-0.25 to -22 V (greater

than lower OK)

Configurable

Lower OK limit

-0.25 to -22 V (less than upper OK)

Accuracy: $\pm 1\%$ of full scale range

Independent 24-bit ADCs on input channels

Supports Bently transducer or 2/3 wires custom transducer for Accelerometers, Velomitor and Proximitors.

Speed/Keyphasor

Keyphasor transducers support multiple events per revolution and event ratios for speed inputs up to 20 kHz.

Threshold voltage resolution

0.1 Vdc

Interfaces

Proximity Transducer Interface

Supply Voltage -22.8 to -25.2 Vdc

Maximum Rated Current

15 mA

Short Circuit Current

15.1 mA to 23.6 mA

Accuracy $\pm 1\%$ of full scale range

Input Impedance 3-wire Voltage Mode, 10 k Ω

RPM range 1 to 120,000

Proximity Switch Interface

Supply Voltage -10 to -24 Vdc

Interfaces

Lower Not Ok limit

-2.75 ± 0.05 V

Rpm range 1 to 60,000

Other Inputs

Magnetic Pick up

Input voltage Adapt to sensor 284947

output

RPM range 200 to 120,000

Contact Inputs

Monitor provides 3 contact capabilities with input terminals

Configuration lock

Latched alarm/relay reset function

Monitor Bypass

Activate 0 to 10 k Ω

De-activate 150 k Ω to infinite

Button Inputs

External button to reset latched alarm and relay

One buried button

provides 3

functions

I Display monitor

information

I LCD contrast

adjustment

I Reset settings to default

Display Monitor Information

Reset listed

settings to

Default

I User account name

I IP Address

I FW/HW version

Jumper Between COM & Chassis GND

Jumpers are 2-pin terminal interfaces that

connects COM to the Chassis ground (GND).

Alternatively, COM can be connected to an

earth ground separately through a terminal.

Outputs

Buffered Output

Three buffered

outputs are available

on the monitor

through BNC

connectors

2 Vibration Outputs

1 Speed Output

Relays

Relays provide two

dry-contact outputs

May be normally

energized or

de-energized

No output feedback

determination

Relay Circuit Specification in

Non-Hazardous Area

Type Single pole, double

throw

Sealing Epoxy sealed

Contact life 100,000 cycles @ 5

amps

250 Vac

200,000 @ 1 amp, 24

Vdc

Insulationresistance 1000 MΩ minimum @

500 Vdc

Relay closed contact

resistance

1 Ω maximum

Relay open contact

resistance

1 MΩ minimum

Maximum switched

contact voltage

250 Vac / 250 Vdc

Maximum breaking

contact current

6 A @250 Vac / 6 A

@24 Vdc

Maximum switched

power

1500VA AC / 150 Watts

DC

Relay Circuit Specification in

Hazardous Area

Maximum

switched

contact

voltage and

current

6 A @24 Vac / 5 A @ 30 Vac /

5.8 A @24 Vdc / 4 A @30 Vdc

SPA Output (2300/25)

Input signal

range

High AC: 8 Vpp Low AC: 1.6 Vpp

DC GAP: 0 to -20 Vdc (max

measurable AC signal is 1

Vpp).

Accuracy High/Low AC: $\pm 1\%$ of Full-Scale

at 100 Hz DC GAP: ± 0.5 V

(measurable AC accuracy:

± 20 mV)

Frequency

response

10 Hz to 3000 Hz $\pm 5\%$

Relay Circuit Specification in

Hazardous Area

LEDs

OK Indicates when the monitor is

operating properly.

Protection

fault

Indicates hardware fault that

is impacting alarm

determination.

User inhibit Indicates the alarm/relays

have been intentionally

inhibited from operation.

Bypass Indicates user initiated bypass

action.

Relay status Indicates if relays have been

activated.

TX/RX Indicates the Ethernet status

and monitor communicating

with remote software.

SPEED/AUX

channel

status

Indicates the speed channel

has valid speed signal input

OR operating correctly when

AUX.

Channel Alarm Status

Alert LED Engages if any channel is in

alert state.

Danger LED Engages if any channel is in danger state.

LCD Display

Allows viewing machine speed, vibration measurements value, setpoints, and configuration information.

Communications

Ethernet Ethernet, 10Base-T and

100Base-TX. Conforms to

IEEE802.3

RJ-45 for 10Base-T/100Base-TX

Ethernet cabling

Cable length: 100 meters (328 ft.)

maximum

Environmental Limits

Operating

Temperature

-30°C to +65°C

(-22°F to +149°F)

Storage

Temperature

-40°C to +85°C

(-40°F to +185°F)

Humidity Up to 95%, non-condensing

Vibration

Limitation

3 g

Battery Life for

Real Time

Clock

Powered: 38 years @ 50°C

(122°F)

Un-powered: 12 years @

50°C (122°F)

Trend Measurements:

Duration Intervals

Pre-Event Data 10 minutes 1 second

20 seconds 100

milliseconds

Post-Event Data 10 seconds 100

milliseconds

1 minute 1 second

Spectrums/Waveforms:

Duration Intervals

Pre-Event Data 2.5 minutes 10 seconds

Post-Event Data 1 minute 10 seconds

In the event of a network disruption between the 2300 and System 1, the

2300 can store up to at least 5 alarm

data captures. (This requires System 1

Evolution 21.1 or newer and Firmware

release 3.2 or newer for 2300.)

Physical

Dimensions

(Width xDepth xHeight)

127 mm x 127 mm x 76.2 mm

(5 in. x 5 in. x 3 in.)

Weight 1.03 kg (2.26 lbs)

Mounting Panel mount or DIN rail

(adapter included)

